



MYX KRONOZ 

SMARTWATCH

DESIGNED IN SWITZERLAND

ZeClock

ENGLISH

CHARGING	04	RECORDER	13
PAIRING	06	PEDOMETER	13
DISPLAYS	09	FIND MY PHONE	14
CALLS	10	CAMERA REMOTE	14
NOTIFICATIONS	11	ANTI-LOST ALERT	14
VOICE CONTROL	12	TECH SPECS	15

OVERVIEW



TOP KEY

LONG PRESS Power ON / OFF

LONG PRESS Exit menu

LONG PRESS 5-8s Reset

PRESS 1 X Scroll through menu icons

PRESS 1 X Answer incoming call

PRESS 1 X Light up the screen

BOTTOM KEY

PRESS 1 X Enter selected menu

PRESS 1 X Start a function

PRESS 1 X Reject incoming call


PRESS 1 X End current call

PRESS 1 X Light up the screen



To set the time, gently pull out the crown, turn it, and push it back. ZeClock will automatically sync the date of your paired mobile device once you have installed ZeClock App on your smartphone (iOS 7+ and select Android 4.3+ devices with Bluetooth 4.0)

1. CHARGING



Charge ZeClock for two hours before your first use.

1. Put the charging cradle beneath the watch
2. Make sure the 4 pins on the cradle fit correctly onto the charging terminals on the left side of ZeClock
3. Connect the charging cradle with the USB cable
4. Plug the big end of the USB cable to a power source
5. A battery indicator will fill to indicate charging is in progress. Once ZeClock is charged, the battery indicator will be full

2. PAIRING

When using ZeClock for the first time, you must pair it to your phone via Bluetooth. Bluetooth is on by default.

- Enable Bluetooth on your mobile device
- Select **ZeClock** in the list of devices
- A paired icon on ZeClock display and a gentle vibration will confirm successful pairing



You only need to pair your device once. After the initial pairing, ZeClock will automatically connect to your phone as long as it is turned on and within range. To pair ZeClock to another device, repeat the same steps

System Requirements

iOS 7+

iPhone 4s, 5, 5c, 5s, 6, 6 Plus.
iPad (3rd, 4th and 5th generation)
iPad Mini, iPod touch (5th generation)

SELECT ANDROID 4.3 +

ZeClock app is available for select
Android 4.3 + devices that support
Bluetooth 4.0

Visit www.mykronoz.com to get the latest compatibility list.

Search for **ZeClock App** in the App store or Google Play, download and install the App on your mobile device.



i

ZeClock will sync the notifications of SMS, emails, social media, calendar events, and personal life reminders once ZeClock App has been successfully installed on your smartphone. Please note some features will not work unless ZeClock App has been installed on your smartphone

3. DISPLAYS

Homepage



Bluetooth is ON



Device is connected



Voice Control



Recorder



Pedometer



Notifications



Call history



Find my phone



Camera remote



Anti lost alert



Incoming call



4. CALLS

After a successful Bluetooth pairing with your smartphone, Bluetooth calls feature is on. You can answer and make phone calls from ZeClock.

ANSWER AN INCOMING CALL

Press 1 X the TOP KEY

END CURRENT CALL

Press 1 X the BOTTOM KEY

REJECT AN INCOMING CALL

Press 1 X the BOTTOM KEY

MAKE A CALL

User can make calls from the **Call History** panel. Single Press BOTTOM KEY to enter the menu. Single press TOP KEY to select a record. Press BOTTOM KEY to call the selected contact. Short press BOTTOM KEY to end the call.



5. NOTIFICATIONS

After successful Bluetooth connection and installation of ZeClock App on your smartphone, ZeClock will show notifications of SMS, emails, social media, calendar events, and personal life reminders. On ZeClock App, tap **Notifications** tab to select the notifications you want to receive onto your watch. If you wish to disable certain notifications, swipe the selection button to the left.

Setting up notifications for iOS users:

- Go to the Settings of your iOS device
- Tap "Notification Center"
- Select which type of notifications you wish to receive on ZeClock
- Enable "Show in Notification Center" to receive the notification on ZeClock



The total number of notifications will be displayed on the Notifications panel of ZeClock. Single press BOTTOM KEY to view the notifications list, another single press to clear the data. Long press TOP KEY to exit

6. VOICE CONTROL

Use the **Voice Control** feature to voice command your mobile device remotely or search information from the Internet.

On the **Voice Control** panel, single press BOTTOM KEY to turn on **Voice Control**, another single press to switch between start and stop. Long press TOP KEY to exit the menu.

Examples of what you can ask or do:

- Call (name of your contact)
- Send a SMS to (name of your contact)
- What's the weather like?
- Set an alarm for tomorrow 5 am



This feature is available with iOS 7+ devices that support Siri and Select Android 4.3 + devices that support Google Now. To use voice control, your smartphone must have access to the Internet using either 3/4G or Wifi

7. RECORDER

On the **Recorder** panel, single press **BOTTOM KEY** to enter the menu. Short press **TOP KEY** to scroll between **Record** and **Play**. Single press **BOTTOM KEY** to select **Record** and start recording your voice memo. Press **BOTTOM KEY** to switch between **Recording** and **Saved** file. If you select the **Play** button, single press **BOTTOM KEY** to **Play** or **Pause** the latest record. Long Press **TOP KEY** to exit the menu.



Only 1 recording file can be saved

8. PEDOMETER

On the **Pedometer** panel, single press **BOTTOM KEY** to enter the menu. Short press **BOTTOM KEY** to turn on the pedometer, another press to turn off or pause. Long press **TOP KEY** to exit the menu.



The pedometer automatically resets at midnight

9. FIND MY PHONE

On the **Find my phone** panel, single press BOTTOM KEY to enter the menu. Short press BOTTOM KEY to start finding your phone. This operation will make your phone ring. Long press TOP KEY to exit the menu.

10. CAMERA REMOTE

On the **Camera Remote** panel, single press BOTTOM KEY to enter the menu. [iOS users] Short press TOP KEY to take pictures while the camera on your paired smartphone is on. [Android users] the key setting depends on which volume key is defined for quick camera shooting on your Android device. If it is volume + key: single press TOP KEY; if it is volume - key: single press BOTTOM KEY. Pictures will be saved in the smartphone. Long press TOP KEY to exit the menu.

11. ANTI-LOST

This option can be enabled from ZeClock App. If **Anti-Lost** option is on, ZeClock will alert you when your paired device leaves the Bluetooth operating range (10 meters).

12. TECH SPECS

Dimensions	45*15.2 mm
Weight	65 grs
Bluetooth	BLE 4.0
Battery type	Li-ion 200 mAh
Watch movement battery type	SR626W
Watch movement battery life	2 years
Talk time	2-3 hours
Standby time	4 days
Charging time	1 hour
Movement	Quartz
Display	OLED 96*32 pixels
Sensor	6-axis accelerometer
Operating temperature	-10°C to +60°C
Water resistance	IP 54
International warranty	1 year

ABOUT THIS MANUAL

The features of ZeClock and the contents of the user manual are subject to change. To get the latest instructions on how to use this product, please refer to the online user manual available on www.mykronoz.com

SUPPORT

If you have any question or require assistance regarding our product, please visit www.mykronoz.com/support/ or email us at support@mykronoz.com