



MY X KRONOZ 

SMARTWATCH

DESIGNED IN SWITZERLAND

ZeWatch³

ENGLISH

CHARGING	06	SLEEP	15
PAIRING	07	GOALS	16
DISPLAYS	11	REMINDERS	17
CALLS	12	VOICE CONTROL	18
NOTIFICATIONS	13	MUSIC	19
ACTIVITY	14	ANTI-LOST ALERT	19

OVERVIEW



To get the most accurate data we recommend wearing ZeWatch³ on your non-dominant hand and not too loose

NAVIGATE THE TOUCHSCREEN

DOUBLE TAP light up the screen

SWIPE UP OR DOWN navigate through the activity and sleep screens

LEFT button

- PRESS + HOLD** activate pairing mode
- PRESS 1 x** reject incoming call
- PRESS 1 x** end current call
- PRESS 1 x** volume -
- PRESS 2 x** redial last number


RIGHT button

- PRESS + HOLD** turn ON / OFF
- PRESS 1 x** light up the screen
- PRESS 1 x** answer incoming call
- PRESS 1 x** volume +
- PRESS 1 x** home screen / exit
- PRESS 2 x** activate voice control



To reset ZeWatch³ to its original settings, press and hold the **RIGHT** and **LEFT** buttons simultaneously.

1. CHARGING



Charge ZeWatch³ for two hours before your first use.

1. Gently push the clasp of your ZeWatch³
2. Plug the USB end into the USB port of a computer

Tip: To easily connect ZeWatch³ to a power source, we recommend using the USB extension cable provided

3. A battery indicator will fill to indicate charging is in progress
4. Once ZeWatch³ is charged, the battery indicator will be full



A full charge takes 1h30. When the battery level gets low, a low battery indicator will appear

2. PAIRING

The first time you use ZeWatch³, a **SET UP** message will prompt you to set up your ZeWatch³ using a mobile device or a computer.

GET ZeWatch³ APP

[iOS & Android users] Search for ZeWatch³ App on the App store or Google Play Store.

[Windows Phone users] Search for ZeWatch³ App on the Windows Phone Store.



System Requirements

iOs

iOS 7+ devices with Bluetooth 4.0 BLE
iPhone 4s, 5, 5c, 5s, 6, 6 Plus, iPad (3rd, 4th
and 5th gen) iPad Mini, iPod touch (5th gen)

Android



Select Android 4.3 +
devices that support
Bluetooth 4.0 BLE

Windows Phone

Select Windows
Phone 8.1 that support
Bluetooth 4.0 BLE

Visit www.mykronoz.com to get the latest compatibility list

Step 1 : Pairing through the application (Bluetooth Low Energy - BLE)

1. Enable Bluetooth on your mobile device
2. Open [ZeWatch App](#) on your mobile device. [Sign up](#) if you are a new member or [Log in](#) with your existing account. After entering your personal information, select your ZeWatch model and tap Set up
3. Make sure ZeWatch³ is nearby and select [ZeWatch³ BLE](#) in the list of devices
4. You will receive a pairing request on your mobile device. Press Pair to accept it
5. Then, a pairing request will appear on your ZeWatch³ display. Press ZeWatch³ **LEFT** button to accept the pairing 
6. When ZeWatch³ is successfully paired, you will be notified on ZeWatch³ and on your mobile device's screen 

This operation will allow you to synchronize time, date, activity and sleep data, reminders and notifications.



You can also set up your ZeWatch³ using our Mac or PC software available on MyKronoz website: <http://www.mykronoz.com/support/>

System requirements : Windows 7,8,XP – MAC OSX 10.8 and above

Step 2 : Manual Pairing (*Bluetooth Classic*)



1. From ZeWatch³ homescreen page, hold and press the **LEFT** button until a phone icon appears



2. Go to your mobile device's Bluetooth settings and select ZeWatch³ in the list of devices



3. A phone icon will be displayed on ZeWatch³ and a beep will sound to confirm successful pairing

This operation will allow you to make and receive calls with ZeWatch³



If pairing fails repeat the same steps. Pairing is a one-time process. If you want to pair your ZeWatch³ with another account, you first need to unpair from the current one. On ZeWatch App, go to Settings > Set up ZeWatch³ > Unpair. Tap Set up ZeWatch³ to pair a new device

3. DISPLAYS

Home screen



Pairing



Redial



Syncing



Failed pairing



Voice control on



Upgrading



Incoming call



Voice control off



Disconnected



Missed Call



Memory full



ZeWatch³ will automatically sync the time and date of your paired mobile device (iOS7 + / select Android 4.3 + / select Windows Phone 8.1 + only). You can set your preferred time and date format manually in the Settings tab of ZeWatch³ App. Make sure you keep the device charged to avoid the time being reset

SMS



Day mode



Distance



2.54

Email



Sleep mode



Sleep



10:10:12

Social Media



Steps



1254

Goal achieved



GOAL ACHIEVED

Calendar Event



Calories



242

Low power



LOW POWER

4. CALLS

After a successful Bluetooth pairing with your phone, Bluetooth call feature is on.

ANSWER AN INCOMING CALL

Press 1 X the **RIGHT** button

DECLINE AN INCOMING CALL

Press 1 X the **LEFT** button

MUTE AN INCOMING CALL

DOUBLE TAP the screen

END CURRENT CALL

Press 1 X the **LEFT** button

REDIAL LAST NUMBER CALLED

Press 2 X the **LEFT** button

ANSWER A NEW INCOMING CALL AND PUT ON HOLD ON THE ORIGINAL CALL

Press 1 X the **RIGHT** button

HANG UP THE ORIGINAL CALL AND ANSWER A NEW INCOMING CALL

Press + hold the **RIGHT** button

REJECT AN INCOMING CALL WHILE A CALL IS IN PROGRESS

Press 1 X the **LEFT** button

ADJUST THE VOLUME DURING A CALL

DOUBLE TAP to access volume control

Press the **LEFT** button to decrease -

Press the **RIGHT** button to increase +

5. NOTIFICATIONS

ZeWatch³ shows notifications of incoming and missed calls, SMS, email, social media activity, calendar events and anti-lost alert*. Open ZeWatch³ App, tap **Settings** > **Notifications** to select the notifications you want to receive onto your ZeWatch³. If you wish to disable certain notifications, swipe the selection button to the left.

Press ZeWatch³ button to dismiss the notification. If not dismissed, the notification will reappear next time you wake up the screen.

Setting up notifications for iOS users


- Go to "Settings" of your iOS device
- Tap "Notifications"
- Select which type of notifications you wish to receive on ZeWatch³
- Enable "Show in Notification Center" to receive the notification on ZeWatch³



*Windows Phones may not support those features, please contact support@mykronoz.com for more information

6. ACTIVITY

ZeWatch³ tracks the number of steps taken, distance travelled and calories burned throughout the day. You can view your daily activity in-real-time on ZeWatch³ display by swiping down the touchscreen.



You can also view your activity data and history on the [Activity](#) tab of ZeWatch³. On the main [Activity](#) screen you can check your performance level against your daily goals. Click on any activity bar to get a detailed graph of your daily, weekly and monthly performance.

i ZeWatch³ show daily data. The activity tracker resets at midnight. To upload your latest activity data do not forget to tap the sync icon in the upper right hand corner of ZeWatch app

7. SLEEP

ZeWatch³ tracks the hours slept and the quality of your sleep (light sleep, deep sleep, awake times)

■ START/ EXIT SLEEP MODE

To start sleep mode, open ZeWatch³ App, tap on the bottom purple sleep bar, click on [Add sleep > Start Sleep now](#)

To end sleep mode, open ZeWatch³ App, tap on the bottom purple sleep bar, click on [Add sleep > Awake](#)

■ PRESET SLEEP

Open ZeWatch³ App > Go to [Settings > Advanced Settings](#) > Click on [Preset sleep](#) to enter your desired bed and wake up times. By default, ZeWatch³ will track your sleep from 11pm until 7am.

i To upload your latest sleep data, do not forget to tap the sync icon in the upper right hand corner of ZeWatch³ App. If you forget to activate sleep mode, you can manually add sleep logs in ZeWatch³ App. Open ZeWatch³App, click on [Add sleep > Add sleep](#)

8. GOALS

Tap the **Goals** tab of ZeWatch³ App to set daily goals for steps taken, distance travelled, calories burned and hours slept. Click on the sync button in the upper right corner to save your goals.

Once you hit one of your daily goal, ZeWatch³ will gently vibrate and display a Goal achieved icon



You can modify your daily goals value at any time from ZeWatch³ App. Do not forget to tap the sync icon to save your new goals. [iOS users] Press ZeWatch³ RIGHT button to light up the screen and initiate syncing

9. REMINDERS

Tap the [Reminders](#) tab of ZeWatch³ App to add daily life reminders. You can set up to 6 daily reminders, and choose the type of reminder and preferred time and day. ZeWatch³ will gently vibrate and display the corresponding reminder icon to alert you. Press ZeWatch³ button to dismiss the reminder. If not dismissed, the same alert will repeat after two minutes.



10. VOICE CONTROL

Use the voice control feature to voice command your mobile device remotely or search information from the Internet. Double press the **RIGHT** button to initiate voice control and speak your command. Press the **RIGHT** button to disconnect voice control

Examples of what you can ask or do:

- Call (name of your contact)
- Send a SMS to (name of your contact)
- What's the weather like ?
- Set an alarm for tomorrow 5 am



This feature is available with iOS 7+ devices that support Siri, Select Android 4.3 + devices that support Google Now or S Voice, Select Windows Phone 8.1+ with Cortana. To use voice control, your mobile device must have access to the Internet using either 3/4G or Wifi

11. MUSIC

Once Bluetooth pairing has been carried out, you can stream music stored on your paired mobile device through ZeWatch³.

12. ANTI-LOST ALERT

When your paired device leaves the Bluetooth operating range (5 meters) ZeWatch³ will trigger a vibrating notification to inform you that your device is away. Press ZeWatch³ button to dismiss the alert.



The features of ZeWatch³ and the contents of the user manual are subject to change. To get the latest instructions on how to use this product, please refer to the online user manual available on www.mykronoz.com

13. TECH SPECS

Size	14,7 x 8,6 x 5,8 cm
Weight	41 gr
Bluetooth	2.1 & 4.0
Battery type	Li-ion 200 mAh
Battery life	up to 4 days
Charging time	1h30
Memory	5 days of activity
Display	Touchscreen OLED 96 * 64
Sensor	3-axis accelerometer
Operating temperature	-10°C to +60°C
Water resistance	Sweat, rain and splash resistant
International warranty	1 year



If you have any question or require assistance regarding our product, please visit www.mykronoz.com/support or email us at support@mykronoz.com